


2161 - BLACK ONE



900TXB-42R



SUB 44R



TXB 44R



Programmazione radiocomando

1. Premere e mantenere premuti contemporaneamente i tasti A e B del BLACK ONE finché il led inizia a lampeggiare; rilasciare i tasti.
 2. Posizionare i radiocomandi come in figura 2 e premere il tasto del radiocomando originale da duplicare finché il led del BLACK ONE inizia a lampeggiare rapidamente.
 3. Con il led del BLACK ONE lampeggiante, premere il tasto dove si vuole programmare il tasto appena acquisito.
- PS: Per programmare i restanti tasti ripetere la procedura precedente.*

Programmazione a distanza

1. Posizionarsi nel raggio di ricezione della centralina.
2. Tenere premuto per almeno 15s il tasto di un radiocomando originale precedentemente programmato sul ricevitore. Rilasciare il tasto.
3. Premere (entro 10s) il tasto del BLACK ONE programmato.

Programmazione sulla centralina

1. Premere una volta il pulsante P sul ricevitore, il led inizierà a lampeggiare per 10s.
2. Premere una volta il tasto del BLACK ONE programmato, attendere che i led LR1 e LR2 si accendano a luce fissa per 2s.

RadioreMOTE programming

1. Simultaneously press and hold in the A and B buttons of the BLACK ONE until the LED begins to flash.
 2. Place the radioreMOTES as in figure 2 and press the key of the original radioreMOTE to be duplicated until the led of BLACK ONE starts blinking quickly.
 3. While the led of BLACK ONE is blinking, press the key where you want to program the key just acquired.
- P.S.: Please repeat the previous procedure to program the remaining keys.*

Remote programming

1. Place yourself inside the reception range of the central unit.
2. Hold down the key of an original radioreMOTE previously programmed on the receiver for at least 15secs. Release the key.
3. Press the programmed key of BLACK ONE within 10secs.

Programming on the central unit

1. Press once the P key on the receiver, the led will start blinking for 10secs.
2. Press once the programmed key of BLACK ONE. Wait for the LR1 and LR2 leds to turn on steadily for 2secs.